

# PRODUCT NUMBER: 1011145 Clarity C2 Multiposition Earmuff

Learn more about our products at howardleight.com >
Learn more about hearing conservation at hearforever.org >



# Overview

### **Reference Number**

1011145

#### **Product Type**

Hearing Protection

# Range

Earmuffs

#### Line

Sound Management Earmuffs

#### Brand

Howard Leight by Honeywell

## Brand formerly known as

BILSOM

#### Industry

# **Product Use**

Sound Management

# **Features & Benefits**

#### Feature

SOUND MANAGEMENT TECHNOLOGY Enhances on-the-job communication through uniform attenuation. Clarity blocks noise while voice, signal, alarm and other high frequencies can be heard more naturally, with less distortion, combating overprotection and worker isolation. DIELECTRIC/PLASTIC CONSTRUCTION Clarity's robust nondeforming dielectric

# Clarity C2 Multiposition Earmuff - 1011145

construction withstands use and abuse, while protecting your workers in electrical environments. MULTIPLE-POSITION WEAR Clarity C2 allows flexibility in wear as an over-the-head, behind-the-head or under-the-chin earmuff. Clarity C2 can be worn with other PPE including visors, face shields, respirators and welding shields. A headband strap provides additional security, keeping earcups in place when worn other than above the head. NON-DEFORMING OUTER HEADBAND Clarity's non-deforming outer headband provides better comfort, minimizes pressure on head, withstanding rough treatment in the toughest workplaces. QUICK-CLICK HEIGHT ADJUSTMENT Height adjustment remains fixed during wear. SNAP-IN EAR CUSHIONS Make replacement quick and easy. INCLUDES HEADBAND STRAP

#### **Benefit**

The patented Clarity Sound Management technology improves worker safety by blocking noise, while voice and signal frequencies can be heard more naturally. Clarity earmuffs provide uniform attenuation that allows speech frequencies to be heard with less distortion - combating worker isolation and overprotection on the job. Plus, Clarity's robust non-deforming dielectric design withstands use and abuse, while protecting workers in electrical environments.

# **Technical Description**

SNR (dB)

30

H (dB)

30

M (dB)

29

L (dB)

25

#### **Attenuation Data**

Frequency (Hz) Frequenz (Hz) Fréquence (Hz)631252505001000200040008000Mean Attenuation (dB) Mittlere Dämmung (dB) Atténuation moyenne (dB)16.920.729.535.231.032.135.831.1Standard Deviation (dB) Standardabweichung (dB) Déviation standard (dB)4.43.13.22.32.72.03.53.8Assumed Protection (dB) Angenommener (dB) Protection supposée (dB)12.417.626.329.928.330.032.327.3

#### **Earmuff Construction**

Plastic [or Dielectric]

## Other Material

LDPE, POM, PA, EPDM, PP, PUR-E, PVC

## Dielectric

Yes

# Color

Black and Light Metallic Blue

## **Batteries Needed**

None

## Weight (grs)

208

#### **Design Patents**

Clarity Sound Management Technology

### **Headband Style**

Multiple-Position

# **Sound Amplification**

No

#### AM/FM Radio

No

# **Automatic Shut-Off Function**

140

# **Audio Input Jack**

No

#### **Hi-Visibility**

No

# **Certifications**

E.C. Declaration of Conformity

**EC Category PPE** 

2

Quality Assurance ISO 9001 / 2000

**EC Certificate Number** 

0301137

**EC** Attestation

EC Attestation

**EC Attestation Number** 

200322880

# **Maintenance**

#### Life Cycle

Cushions should be replaced periodically to retain maximum attenuation. Use the following as a guideline for replacement of ear cushions and insert foam. General use and wear - Ear cushions and foam inserts should be replaced at least every 6 months. Heavy use or wear in humid/extreme climates - Ear cushions and foam inserts should be replaced at least every 3 months. Cracking or leakage is visible - replace ear cushions and foam inserts immediately.

## **Storage Information**

When not in use, the earmuffs should be stored in a clean dry container or locker. Do not use solvents or petroleum-based products. Do not immerse the earmuffs in water.

#### **Care Instructions**

Earmuffs are an important safety product and should be inspected regularly. Its use, care and maintenance are critical to its effective performance. Earmuffs and in particular ear cushions may deteriorate with use and should be examined at frequent intervals for cracking and leakage. If the ear cushions become hard, damaged or deteriorated, they should be replaced promptly using recommended Hygiene Kits. Earmuffs should be maintained by regular cleaning. Use a mild disinfectant solution. A gentle wipe is all that is required.

# Parts & Accessories

#### **Accessories**

Hygiene Kit - Packed in a plastic bag, including two ear cushions and two liners. Ref. # 1006017 for C2

Beltclip - For carrying purpose. Old Ref. # 1000252 New Ref. # 1016730 Cool II Pads - Sweat absorbing pads. Ref. # 1000365 5-pair, Ref. # 1000364 100-pair

Optisorb - cotton sleeve slides over earcup. Ref. # 3302101

Polar Hood - Ref. # 1016870 Lg/XLg; Ref. # 1016871 Sm/Med

# **Packaging**

**EAN Code** 

7312550111451

© Honeywell International Inc.