## Honeywell | Safety Products





PRODUCT NUMBER: 1017291

### **Forestry Kit**

Learn more about our products at howardleight.com > Learn more about hearing conservation at hearforever.org >



# Overview

#### **Reference Number**

1017291

#### **Product Type**

Hearing Protection

#### Range

Earmuffs

#### Line

Noise Blocking Earmuffs

#### **Brand**

Howard Leight by Honeywell

#### Industry

Agriculture
Green Spaces
Wood Industries

#### **Product Use**

Ideal for forestry activities

#### Forestry Kit - 1017291



This Forestry kit is equipped with: Leigthning L1H earmuffs (#1012539) provide superb benefit comfort and protection against hazardous noise, features patented Air Flow Control™ technology for optimal attenuation accross all frequencies. SNR28. Bright orange polyethylene helmet increases visibility in the field. Light weight and vented on the top, it is ideal for outdoor work. Also featuring a rain gutter, this new helmet is made for outside applications. Fully equipped with a 6 points harness, it is also very comfortable. Mesh faceshield (#1017800) is durable, flexible and easy to adjust (flip-up-and-down). Detachable brim / sun peak. Integrated neckguard protects from debris and sun/rain.

#### **Technical Description**

SNR (dB)

28

H (dB)

31

M (dB)

25

L (dB)

19

**Earmuff Construction** 

Metal

Dielectric

No

Weight (grs)

701

**Sound Amplification** 

No

AM/FM Radio

No

**Automatic Shut-Off Function** 

No

**Audio Input Jack** 

No

**Hi-Visibility** 

No



E.C. Declaration of Conformity

**EC Category PPE** 

2


**Quality Assurance** 

ISO 9001 / 2000

**EC** Attestation

EC Attestation

#### Forestry Kit - 1017291



We're sorry, there are no images available at this time.



#### Life Cycle

Examine the faceshield before use. Damaged helmet, carriers or faceshields which show scratches, crackas, broken mesh or other types of defects shall be replaced.

#### **Storage Information**

Before and after use, store in temperature range from -30°C to +50°C.

#### **Care Instructions**

Clean with mild soap only, do not use detergents.

© Honeywell International Inc.